

MOTOR HP	VOLTS	LOAD AMPS	FUSE MAX SIZE	CIRCUIT BREAKER	SERVICE DISCONNECT AMPS
3 HP	3/208	10.6	15	20	30
	3/230	9.6	15	20	30
	3/460	4.8	10	15	30
5 HP	3/208	16.7	30	40	30
	3/230	15.2	25	40	30
	3/460	7.6	15	20	30
10 HP	3/208	30.8	50	80	60
	3/230	28	50	70	60
	3/460	14	25	35	30
15 HP	3/208	46.2	60	90	60
	3/230	42	60	90	60
	3/460	21	30	40	30
20 HP	3/208	59.4	100	125	100
	3/230	54	90	125	100
	3/460	27	45	60	60
30 HP	3/208	88	150	225	200
	3/230	80	150	200	200
	3/460	40	70	100	100
50 HP	3/208	143	250	350	400
	3/230	130	225	350	400
	3/460	65	100	150	100
3/4 HP	1/120	13.8	20	20	30
	1/230	6.9	10	15	30
3 HP	1/208	18.7	30	45	30
	1/230	17	25	40	30
5 HP	1/208	30.8	50	80	60
	1/230	28	45	70	60
10 HP	1/208	55	100	125	100
	1/230	50	90	125	100